



Luz de seguridad solar con batería de reserva

PILAS

Use 4 pilas D para encenderla o como respaldo para el panel solar; las pilas no están incluidas. Cuando las reemplace, no coloque pilas nuevas con pilas viejas.

1. Retire el soporte de montaje deslizándolo hacia abajo. (Imagen 1)
2. Afloje el tornillo de la tapa del compartimiento para pilas con un destornillador de cabeza plana o un destornillador de cabeza Phillips n.º 1.
3. Libere cada pinza y retire la tapa del compartimiento para pilas.
4. Coloque 4 pilas D (no incluidas); tenga en cuenta los polos. Vuelva a colocar la tapa del compartimiento para pilas ajustando el tornillo en su lugar, no apriete demasiado. (Imagen 2)

LUZ DE SEGURIDAD

Monte la luz de seguridad en paredes o aleros. Para obtener el mejor rendimiento, instale a 2,4 m (8 pies) sobre el nivel del suelo como mínimo. Asegúrese de que el área de montaje esté seca y limpia de residuos.

1. Sostenga la cubierta trasera/el soporte de montaje en su lugar y marque la ubicación de cada tornillo o use la plantilla incluida.
2. Taladre orificios piloto con una broca de 3/16".
3. Inserte los tacos incluidos.
4. Instale la cubierta trasera/el soporte de montaje con los tornillos incluidos y un destornillador Phillips n.º 1; no apriete demasiado.
5. Vuelva a colocar la luz de seguridad en el soporte de montaje, asegurándose de que las pinzas encajen en su lugar.

PANEL SOLAR

Al instalar, asegúrese de que no haya objetos que obstruyan la exposición total a la luz solar del panel. Una carga diaria completa puede tardar hasta 7 horas.

1. Marque las ubicaciones de montaje de la base del brazo corto o largo utilizando los orificios para tornillos como guías.
2. Antes de perforar, verifique que las áreas marcadas estén libres de obstáculos como cables y líneas eléctricas.
3. Perfore un orificio piloto con una broca de 3/32" y fije la base con los tornillos y tacos incluidos.
4. Alinee el panel solar con la parte superior del brazo de montaje y ajuste el ángulo para una exposición óptima a la luz solar. (Imagen 3) Asegúrelo al brazo con la tuerca de mariposa provista.
5. Enchufe el cable USB-A de 4,57 m (15 ft) en el panel solar y la luz de seguridad.

Nota: Si enchufa el cable USB-A en un puerto o tomacorriente USB, asegúrese de que sea una fuente de alimentación de 5 V, 2 A.

OPERACIÓN

Panel solar: Presione el botón en la parte posterior del panel solar para encender la luz de seguridad. La luz de seguridad consumirá energía del panel solar antes de consumir energía de las pilas.

Sensor de movimiento: La luz se enciende en condiciones de poca luz cuando se detecta movimiento en un rango de 7,62 m (25 ft) y 120°, y se apaga cuando ya no se detecta movimiento.

Cabezales ajustables: Gire los cabezales de la luz de seguridad para dirigirlos hacia donde necesita la mayor cobertura.

PROYECTOR O REFLECTOR

Coloque o retire las lentes esmeriladas incluidas sobre cada cabezal para alternar entre los modos de reflector y proyector.

Proyector - Cuando desea una luz más brillante

- Sin las lentes colocadas, la luz brilla en un área concentrada. (Imagen 4)
- Cuando retire la lente, use suavemente un destornillador de plano para sacarla de su lugar. (Imagen 5)

Reflector - Cuando desea una luz más difusa

- Con la lente colocada, la luz difusa brilla en un área más amplia.
- Al colocar la lente, asegúrese de que los orificios de la lente estén en el costado de la lámpara y que encaje firmemente en su lugar.



Figure 1



Figure 2



Figure 3



Figure 4



Figure 5

⚠ ADVERTENCIA

RIESGO DE DESCARGA ELÉCTRICA

- NO SUMERGIR.
- NO USE CERCA DE PECERAS.
- EL PANEL SOLAR ES UN PRODUCTO PARA LUGARES HÚMEDOS Y NO TIENE PIEZAS REPARABLES.
- ASEGÚRESE DE QUE EL PANEL SOLAR ESTÉ AL MENOS A 5 METROS DE PISCINAS Y SPAS.
- EVITE DAÑAR EL PANEL SOLAR. REVISE QUE EL PANEL SOLAR NO TENGA DAÑOS FÍSICOS U OTROS CAUSADO POR LA EXPOSICIÓN A LOS ELEMENTOS A LA INTemperie.
- REEMPLACE EL PANEL SOLAR SI ESTUVIERA DAÑADO.
- NO LO INSTALE EN LUGARES DONDE PUEDAN PISARLO.
- LOS NIÑOS NO DEBEN JUGAR CON EL PANEL SOLAR.
- USE EL PANEL SOLAR SOLO CON LUCES COLGANTES USB.

⚠ PRECAUCIÓN

- LAS BATERÍAS PUEDEN DERRAMAR LÍQUIDOS NOCIVOS O MATERIALES INFLAMABLES O ESTALLAR CAUSANDO LESIONES Y DAÑOS AL PRODUCTO.
- REEMPLACE TODAS LAS BATERÍAS AL MISMO TIEMPO.
- REEMPLACE LAS BATERÍAS TOTALMENTE DESCARGADAS INMEDIATAMENTE.
- QUITÉ LAS BATERÍAS SI EL DISPOSITIVO NO VA A SER UTILIZADO POR UN TIEMPO LARGO.
- NO SUMERGIR EN AGUA.
- LIMPIAR SOLAMENTE CON UN PAÑO SUAVE Y HÚMEDO.

HECHO EN CHINA

©2021 Energizer. Energizer y algunos diseños gráficos son marcas comerciales de Energizer Brands, LLC y subsidiarias relacionadas, que se utilizan bajo la licencia de Jasco Products Company, LLC.

¿Preguntas? Comuníquese al 1-800-654-8483 entre las 7:00 a.m. y las 8:00 p.m. CST (hora central estándar).

Garantía de 2 años. Visite www.bjiasco.com para conocer los detalles de la garantía.



bjiasco.com/recycle
paper made from 25%
post-consumer waste

ADVERTENCIA: Lea todas las precauciones de seguridad y las instrucciones de instalación detenidamente antes de instalar u operar el equipo.

- No exponga al panel solar al fuego ni al calor intenso.
- No lo sumerja en agua.

INSTRUCCIONES DE LA BATERÍA:

• Este producto contiene una batería de litio recargable. La batería no es reparable. Contacte a Jasco Products si necesita reemplazar la unidad de energía solar.

CUIDADO Y MANTENIMIENTO:

- El panel solar no debe sumergirse en agua ni en otros líquidos. La característica de resistencia al agua sirve para corregir una instalación o, en ciertos ángulos, para la lluvia.
- Para optimizar la efectividad del panel solar, haga lo siguiente: Elija una ubicación para el panel solar donde haya la mayor luz solar posible durante el año. Limpie el panel cada varios meses para eliminar polvo o restos que puedan afectar la eficiencia del panel para recolectar energía solar.



Battery Backup Solar Security Light

See reverse for easy-to-follow instructions and exclusive deals.

Thank you for your purchase!

Instructions made easy



Read instructions or watch easy-to-follow video.

Scan code or visit <https://byjasco.com/57418i>

Exclusive deals



For deals, to register your purchase and to tell us how we're doing, simply scan the code or visit byjasco.com/deals



Discover innovative power solutions at www.byjasco.com/power



Like our product? Leave a review on your favorite retailer website or amazon.com

Having problems? Let us know how we can help.
1-800-654-8483
between 7AM-8PM,
M-F, Central Time.



Energizer

Battery Backup Solar Security Light

BATTERIES

Power or use 4D batteries as a back-up to your solar panel; batteries not included. When replacing, do not mix old batteries with new batteries.

1. Remove the mounting bracket by sliding it down. (Figure 1)
2. Loosen the battery door screw with either a flat-head screwdriver or a #1 Phillips-head screwdriver.
3. Unlatch each clip and remove the battery door.
4. Insert 4 D batteries (not included), noting polarity. Replace the battery door, fastening the screw back into place – do not overtighten. (Figure 2)

SECURITY LIGHT

Mount the security light on walls or eaves. For the best performance, install at least 8ft. above ground level. Ensure the mounting area is dry and clean of debris.

1. Hold the mounting bracket in place and mark the location for each screw.
2. Drill pilot holes using a 3/16in. drill bit.
3. Insert the included anchors.
4. Install the mounting bracket using the included screws and a #1 Phillips-head screwdriver – do not overtighten.
5. Reattach the security light to the mounting bracket, ensuring the clips lock into place.

SOLAR PANEL

When installing, ensure that there are no objects obstructing the panel from full sunlight exposure. A full daily charge will take up to 7 hours.

1. Mark the mounting locations of either the short or long-arm base using the screw holes as guides.
2. Before drilling, check that the marked areas are clear of obstacles such as cables and electrical lines.
3. Drill a pilot hole using a 3/32in. drill bit and secure the base with the included screws and anchors.
4. Align the solar panel with the top of the mounting arm and adjust the angle for optimum sunlight exposure. (Figure 3) Secure it to the arm with the provided wing nut.
5. Plug the provided 15ft. USB-A cable into the solar panel and security light.

Note: If plugging USB-A cable into USB port or outlet, ensure it is a 5V, 2A power source

OPERATION

Solar panel: Press the button on the back of the solar panel to power the security light. The security light will consume power from the solar panel before consuming battery power.

Motion sensor: The light turns on in low light conditions when motion is detected in a 25ft., 120° range and off when motion is no longer detected.

Adjustable heads: Rotate the head of the security light to point where you need the most coverage.

SPOTLIGHT OR FLOODLIGHT

Attach or remove the included frosted lens over the head to alternate between flood and spotlight modes.

Spotlight - When you want a brighter light

- No lens attached, the light shines in a concentrated area. (Figure 4)
- When removing the lens, gently use a flathead screwdriver to pop it out of place. (Figure 5)

Floodlight - When you want a more diffused light

- Lens attached, diffused light shines in a wider area.
- When attaching the lens, ensure the holes of the lens are on the side of the light fixture and that it firmly snaps into place.



Figure 1



Figure 2



Figure 3



Figure 4



Figure 5

⚠ WARNING

RISK OF ELECTRIC SHOCK

- DO NOT SUBMERSE.
- DO NOT USE AROUND AQUARIUMS.
- SOLAR PANEL IS A WET LOCATION PRODUCT AND HAS NO SERVICEABLE PARTS.
- KEEP SOLAR PANEL AT LEAST 16 FEET FROM POOL AND SPAS.
- AVOID DAMAGE TO SOLAR PANEL. INSPECT THE SOLAR PANEL FOR PHYSICAL DAMAGE OR OTHER DAMAGE CAUSED BY OUTDOOR EXPOSURE TO THE ELEMENTS.
- REPLACE THE SOLAR PANEL IF DAMAGED.
- DO NOT INSTALL IN LOCATIONS WHERE SOLAR PANEL CAN BE STEPPED ON.
- CHILDREN SHOULD NOT PLAY WITH SOLAR PANEL.
- ONLY USE SOLAR PANEL WITH SECURITY LIGHT.

⚠ CAUTION

- BATTERIES MAY LEAK HARMFUL LIQUIDS OR IGNITABLE MATERIALS OR EXPLODE CAUSING INJURY OR PRODUCT DAMAGE.
- DO NOT MIX OLD AND NEW OR OTHER BATTERY TYPES.
- REPLACE ALL BATTERIES AT THE SAME TIME.
- REMOVE BATTERIES IF PRODUCT IS TO BE UNUSED FOR EXTENDED PERIOD OF TIME.

MADE IN CHINA

©2021 Energizer. Energizer and certain graphic designs are trademarks of Energizer Brands, LLC and related subsidiaries and are used under license by Jasco Products Company, LLC.

Contact our U.S.-based Consumer Care at 1-800-654-8483 between 7AM-8PM, M-F, Central Time.

2-year warranty. Visit www.byjasco.com for warranty details.



WARNING: Read all safety precautions and installation instructions carefully before installing or operating this fixture.

- Do not expose the solar panel to fire or intense heat.
- Do not immerse it in water.

BATTERY INSTRUCTIONS:

This product contains a rechargeable lithium battery. The battery is non serviceable, please contact Jasco Products for a replacement solar power unit.

CARE AND MAINTENANCE:

- The solar panel is not allowed to dip into water or any other liquid. The water-resistant function is limited to correct installation or within a certain angle in rain.
- To optimize the effectiveness of your solar panel, do the following: Choose a location for your solar panel that gets the most sunlight throughout the year. Wipe the panel every few months to remove dust or debris that might affect the solar energy harvesting efficiency of the panel.